



WE RECOMMEND INSTALLATION OF THIS LIGHTING FIXTURE BE DONE BY A LICENSED ELECTRICIAN.

WARNING *** SWITCH OFF THE MAIN ELECTRICAL SUPPLY FROM THE MAIN FUSE BOX/CIRCUIT BREAKER BEFORE INSTALLATION.

INSPECT ITEM CAREFULLY BEFORE ATTEMPTING TO INSTALL. IF THERE IS ANY DAMAGE OR OBVIOUS DEFECT, DO NOT INSTALL.

ITEM MAY NOT BE RETURNED ONCE IT HAS BEEN INSTALLED.

1. Carefully remove all parts from the carton.
2. Remove mounting plate (A) from base of light fixture (C) by removing ball nuts (D).
3. Affix mounting plate (A) to wall outlet box with mounting screws (B) provided.
4. Place fixture base (C) to wall outlet, mark a point for metal anchor (H) with a pencil. Remove the light fixture.
5. Drill a small hole on the marked point, the hole should be big enough for metal anchor (H). Push the metal anchor (H) into the hole.
6. Attach ground (green or green/yellow) wire to ground wire from wall outlet box (usually green or copper in color), fasten together with a plastic wire connector. Tightly wrap the wire connector with electrical tape, so the end of the connector is sealed. IT IS IMPERATIVE THAT THE OUTLET BOX IN YOUR HOME BE PROPERLY GROUNDED.
7. Connect neutral (white) fixture wire coming from fixture base to neutral (usually white) outlet wire. Fasten both wires together with a plastic wire connector and tightly wrap the wire connector with electrical tape.
8. Repeat the same procedure with the hot (black) wires. Always make sure that no wire strands are left outside the connectors. DO NOT REVERSE THE HOT AND NEUTRAL CONNECTIONS OTHERWISE SAFETY WILL BE COMPROMISED.
9. Attach fixture base (C) to the affixed mounting plate (A) and secure with ball nuts (D).
10. Letting the wood screw (J) pass through the hole of bracket (I) and screw it into metal anchor (H) until tight, then lock the fixture (L) to bracket (I) with thumbscrew (K).
11. Remove socket rings (E) from sockets (G), attach shade (F) onto the threaded section of sockets (G) and secure with socket rings (E).
12. Insert light bulbs (not included) into sockets.
13. Restore power and test fixture. Installation is complete.

*** Clean with a dry, soft cloth only. Use no harsh abrasives or chemical agents.